

Professional wireless microphone

- ▶ Professional audio radio link, ideal for videographers, journalists, vloggers, YouTuber and content creators
- ▶ System of transmitter and receiver in ultra-compact and lightweight design
- ▶ Working range up to 50 m
- ▶ Broadcast quality audio
- ▶ Compatible with all cameras & smartphones (TRS & TRRS)
- ▶ Transmitter with integrated microphone as clip-on as well as belt-pack lavalier microphone



Technical data	Hear:Me Wireless transmitter (TX) and receiver (RX)
Transmission type	2.4 GHz digital frequency, worldwide use
Frequency encrypted signal	2400 ~ 2483.5 MHz yes
Transmission power	+10 dBm
Reception sensitivity	-86 dBm
Antenna	PCB Antenna
Sound delay	< 20 ms
Battery	Built-in Li-Ion battery 330 mAh / 3.7 V
Current input	5 V / 0.2 A (max. 5 V / 2 A)
Battery runtime	5 hours
Operating temperature	0°C ~ 50°C
Dimensions Weight	39 x 22 x 55 mm 30 g

Technical data	Hear:Me Wireless Transmitter (TX)
Polar pattern	Omnidirectional
Frequency response	80 Hz ~ 20 kHz
Maximum Output Level	-14 dBu / +3dBu (open/closed integrated pre-amplifier)
Equivalent input noise	36 dBa at max. gain
Maximum SPL	100 dB SPL (at 1 kHz)
Dynamic range	64 dBa
Interface	External microphone input 3.5 mm TRS

Technical data	Hear:Me Wireless receiver (RX)
Audio output amplitude	+0 dB ~ +12 dB
Interfaces	Audio: 3.5 mm TRS Monitor: 3.5 mm TRS/TRRS

Box Content

1x transmitter, 1x receiver, 1x lavalier microphone, windscreen, 3x TRS-TRRS cable for various devices, 1x USB-C charging cable, 1x reset needle

Subject to technical changes. Camera not included.