Power Adapter 200 W

Power Adapter 200 W

Rollei

- Fast charging thanks to three USB-C ports with 100 W each for single or dual use
- The perfect power distributor for the desktop and on the go
- Advanced security features to protect your devices and yourself
- Universal compatibility thanks to 5-way power. Three USB-C and two USB-A ports to charge all your devices simultaneously
- High & smart power for fast and efficient charging without much waiting time.





Technical Data	
Connections	3x USB-C (each 100 W); 2x USB-A
Display	LED – Output display
Input	100 – 240 V / 50/60Hz / 2.5 A max.
Output	USB-C1 : 3.3 – 21.0 V / 5.0 A, 5.0 V / 3.0 A, 9.0 V / 3.0 A, 12.0 V / 3.0 A, 15.0 V / 3.0 A, 20.0 V / 5.0 A 100.0 W max.
	USB-C2 : 3.3 – 21.0 V / 5.0 A, 5.0 V / 3.0 A, 9.0 V / 3.0 A, 12.0 V / 3.0 A, 15.0 V / 3.0 A, 20.0 V / 5.0 A 100.0 W max.
	USB-C3 : 3.3 – 21.0 V / 5.0 A, 5.0 V / 3.0 A, 9.0 V / 3.0 A, 12.0 V / 3.0 A, 15.0 V / 3.0 A, 20.0 V / 5.0 A 100.0 W max.
	USB-A1: SCP: 5.0 V / 4.5 A, 4.5 V / 5.0 A 22.5 W max.
	USB-A2 : SCP: 5.0 V /4.5 A, 4.5.0 V / 5.0 A 22.5 W max.
	USB-C1+C2: 100.0 W+100.0 W USB-C1+C2+C3: 100.0 W+65.0 W+30.0 W USB-A1+A2: 12.0 W+12.0 W USB-C1+C2+A1: 100.0 W+65.0 W+22.5 W USB-C1+C2+C3+A1+A2: 100.0 W+65.0 W +20.0 W+15.0 W
Power consumption at no load	0.3 W
Dimensions (L x W x H) Weight	12 x 8.5 x 3.5 cm 542 g
What's in the Box and Packaging Details	
What's in the box	Power Adapter 100 W
Packaging dimensions (L x W x H) Weight	XX cm XX kg

Specifications are subject to change without notice. *The Bluetooth® word mark and logos are registered trademarks of the Bluetooth SIG, Inc. and any use of such marks by Rollei is under license. Other trademarks and trade names are the property of their respective owners. *Not included in delivery.

